

4G LTE Module Band and Operators

| Module | Country/Region | Operator* | LTE Band Support |
|----------------------|--------------------|----------------------|------------------|
| 4G LTE Module-E | China Hong Kong | 3 (Three) | B3 |
| | | China Mobile, CSL | B3, B7 |
| | | SmarTone | B3, B8 |
| | Thailand | True Move, DTAC | B1 |
| | | AIS | B1, B3, B8 |
| | South Korea | SKT | B1, B3, B5 |
| | | KT | B1, B3, B8 |
| | | LGU+ | B1, B5, B7 |
| | Other Asia Regions | / | / |
| | Italy | 3 (Tre) | B3, B7 |
| | | Vodafone | B3, B20 |
| | | Wind | B7, B20 |
| | | TIM, TISM, H3G | B3, B7, B20 |
| | UK | 3 (Three), O2 | B3, B20 |
| | | EE | B3, B7, B20 |
| | | Vodafone | B1, B3, B7, B20 |
| | Spain | Yoigo | B3 |
| | | Movistar, Orange | B3, B7 |
| | | Telefonica, Vodafone | B3, B7 |
| | France | Free | B7 |
| Orange, SFR | | B7, B20 | |
| Bouygues Télécom | | B3, B7, B20 | |
| Russia | Yota | B7, B20 | |
| | MegaFon, Beeline | B7, B20 | |
| | VimpelCom, MTS | B7, B20 | |
| | Tele2 | B3, B7, B20 | |
| Other Europe Regions | / | B1, B3, B7, B8, B20 | |
| South Africa | Cell C | B1 | |
| | MTN, NeoTel | B3 | |
| | Vodacom | B3 | |
| 4G LTE Module-A | USA | U.S. Cellular | B12 |
| | | AT&T | B2, B4 |
| | | Cricket Wireless | B2, B4 |
| | | H2O Wireless | B2, B4 |
| | | Google Project Fi | B2, B4, B12 |
| | | T-Mobile, Ting | B2, B4, B12 |
| | | Lycamobile | B2, B4, B12 |

*If your operators are not listed here, please check with them for the frequency they support before purchasing.

| Module | Country/Region | Operator* | LTE Band Support | |
|-----------------------------|------------------|----------------------|----------------------|----|
| 4G LTE Module-A | Canada | Rogers Wireless | B4 | |
| | | Bell Wireless | B4 | |
| | | Videotron, Fido | B4 | |
| | | Public Mobile | B4 | |
| | | Virgin Mobile | B4 | |
| | | Telus | B2, B4, B12 | |
| 4G LTE Module-AU | China Taiwan | T Star | B8 | |
| | | APT | B8, B28 | |
| | | FarEasTone | B3, B28 | |
| | | Taiwan Mobile | B3, B28 | |
| | | Chunghwa Telecom | B3, B7, B8 | |
| | Australia | TPG | B7 | |
| | | NBN & Co | B40 | |
| | | Vodafone | B3, B5 | |
| | | Telstra | B1, B3, B28 | |
| | | Optus, Virgin Mobile | B1, B3, B7, B28, B40 | |
| | New Zealand | 2degrees | B3 | |
| | | Spark, Vodafone | B3, B7, B28 | |
| | 4G LTE Module-AU | Argentina | Nextel AR | B4 |
| | | | Telecom Personal | B4 |
| | | | Movistar AR | B4 |
| Brazil | | Claro, Oi, Vivo | B7 | |
| | | Nextel | B3 | |
| | | TIM | B3, B7 | |
| Chile | | Claro, Entel | B7 | |
| | | Movistar | B7 | |
| | | WOM | B4 | |
| Mexico | | Telcel, Nextel | B4 | |
| | | Movistar | B2 | |
| Other South America Regions | | / | B2, B3, B4, B7, B28 | |
| 4G LTE Module-J | Japan | NTT DoCoMo | B1, B19 | |
| | | Softbank | B1, B8 | |
| | | KDDI | B1, B18 | |
| 4G LTE Module-CE | China | CMCC | B38, B39, B40, B41 | |
| | | Unicom | B1, B3, B5, B8 | |
| | | Telecom | B1, B3, B5, B8 | |
| | India | Aircel | B3, B40 | |
| | | Bharti Airtel | B3, B40 | |

*If your operators are not listed here, please check with them for the frequency they support before purchasing.